

CEILING SPEAKER

CS-3/6/12/20/30/80



FEATURES

CS-3/6/12

- Contains a premium grade speaker unit
- best reliability
- The beautiful and graceful cabinet design
- Easy installing and convenience
- Full Range of 1 way speaker system (6 inch unit)
- Multi-tap switch offers an easy way to change taps on a transformer(CS-6/12)


CS-20/30/80

- Contains a premium grade speaker unit
- best reliability
- The beautiful and graceful cabinet design
- Easy installing and convenience
- 2 Way speaker system (6" -2way coaxial type)
- Multi-tap switch offers an easy way to change taps on a transformer







SPECIFICATIONS

Spec \ MODEL	CS-3	CS-6	CS-12	CS-20	CS-30	CS-80
Rated Power	3W	6W	12W	20W	30W	80W
impedance	COM	COM	COM	COM	COM	COM
	3.3kΩ	1.7kΩ	800Ω	500Ω	330Ω	125Ω
	5kΩ	4kΩ	1kΩ	1kΩ	500Ω	250Ω
	10kΩ	8kΩ	2kΩ	2kΩ	1kΩ	500Ω
Frequency Response	150Hz-15kHz	150Hz-15kHz	150Hz-15kHz	150Hz-20kHz	150Hz-20kHz	150Hz-20kHz
SPL (1W/1M)	91dB	92dB	93dB	92dB	93dB	93dB
Weight(Set)	680g/1.5lb	850g/1.8lb	900g/1.9lb	2kg/4.4lb	2.42kg/5.3lb	3.57kg/7.8lb
Dementions(Set)	230(ø)x100(D)mm/9(ø)x4(D)in			230(ø)x180(D)mm/9(ø)x7(D)in		







* Specifications and design are subject to change without notice.



Polar diagram




Frequency Response



CS-3/6/12/20/30/80


Inserting Speaker Into Ceiling

▶ CS-3/6/12




Ceiling Speaker Part-List/Inserting Speaker Into Ceiling


▶ CS-20/30/80



5	SCREW 1WPTC 4 x 12B	2
4	BKT-RING	1
3	BKT-RAIL	2
2	SET	1
1	GRILL COVER	1
NO	NAME	QTY




※ Ceiling Hole Size : Ø200~Ø205




1. Turn clockwise and fit carefully until approaching ceiling or BKT-RING.
2. Put GRILL-COVER on the hall of SET and press to be combined.

CS-3/6/12/20/30/80



INPUT TERMINAL


▶ CS-3



▶ CS-6/12

COM(-) BLACK
 (+) RED

▶ CS-20/30/80



OUTPUT TERMINAL

▶ CS-6

1.7kΩ (6W) 4kΩ (2.5W) 8kΩ (1.25W)



PA SPEAKER 6W / 2.5W / 1.25W
 The impedance switch selects a different range of values on a transformer

▶ CS-12


800Ω (12W) 1kΩ (10W) 2kΩ (5W)



PA SPEAKER 12W / 10W / 5W
 The impedance switch selects a different range of values on a transformer

▶ CS-20


2kΩ (5W) 1kΩ (10W) 500Ω (20W)



PA SPEAKER 5W / 10W / 20W
 The impedance switch selects a different range of values on a transformer

▶ CS-30


1kΩ (10W) 500Ω (20W) 330Ω (30W)



PA SPEAKER 10W / 20W / 30W
 The impedance switch selects a different range of values on a transformer

▶ CS-80

500Ω (20W) 250Ω (40W) 125Ω (80W)



PA SPEAKER 20W / 40W / 80W
 The impedance switch selects a different range of values on a transformer

Inter-M Corporation

- OFFICE: 653-5 BANGHAK-DONG, DOBONG-KU, SEOUL, KOREA
 - TEL : +82-2-2289-8140~8, FAX : +82-2-2289-8149

- Home page: <http://www.inter-m.com>
 - E-mail: overseas@inter-m.com



NO: 128124

www.inter-m.com