

MODEL NO: LM-8000

NAME: Wall Mounted Remote Control



OVERVIEW

Local control is possible using the LM-8000 wall mounted remote control with selection of local background music source in a remote zone as well as control of its volume. Local input allows for line level signal input as well a microphone.

FEATURE

- Easy integration wiring (power, audio, communications)
- Local microphone input, line input and volume control
- BGM channel selection and volume adjustment
- BGM channel display
- Easy Wall installation in a standard NEMA electrical outlet box

SPECIFICATION

		LM-8000
Audio Output		0dB(Balanced)
Audio Input	Local BGM(LINE)	-10dB
	MIC	-50dB(Balanced)
Frequency Response	BGM(60Hz ~ 15kHz)	± 3 dB
	MIC(100Hz ~ 10kHz)	± 3 dB
S/N	BGM	Better than 75dB
	MIC	Better than 65dB
T.H.D.	BGM	Less than 0.05%
	MIC	Less than 0.05%
Priority Control		Paging MIC > DRP > RM1 > RM2> RM 3> RM 4 > LM-8000 > Main BGM
Serial Interface (RS-422)	Communication Speed	9600 bps
	Communication Distance	Maximum 300m (using UTP Cat5)
Operation Temperature		-10°C ~ +40°C
Power Source		DC 24V, 50mA
Weight (Set)		130g / 0.28lb
Dimensions (Set)		70(W)x114(H)x52(D)mm/2.8(W)x4.5(H)x2.0(D)in

APPLICATION

ideal for applications where BGM distribution and multi-zone paging is required such as Restaurants, Retail store, Malls, Hotels, office, gymnasiums and fitness centers

Related Products

- PX-8000
- RM-8000