

# marantz®

## SR6010

### NETWORK AV RECEIVER WITH WIFI & BLUETOOTH



The new SR6010 builds on last year's SR6009 but is again a giant step beyond its predecessor. Seven discrete amplifier channels, each with 185W of pure power, and a 9.2ch processing capability with 13.2ch pre-outs offer extreme versatility for the home cinema enthusiast. With the latest decoding technologies Dolby Atmos and DTS:X (via update later in 2015) you will be flooded with nothing less than a new surround sound sensation. With 8 HDMI inputs (including 1 conveniently located on the front panel) and 2 HDMI outputs, the SR6010 features an advanced video processing system. Prepared for the future, it is equipped to handle 4K Ultra HD full rate 60 Hz content, 4:4:4 Pure Color sub-sampling and 21:9 aspect ratio pass-through. It's also HDCP 2.2 compliant, which is a requirement for 4K Ultra HD copy-protected content. What's more, because we have also upgraded to Audyssey MultEQ XT32 / LFC Pro you get an even more accurate calibration of the speaker to guarantee that every seat in the room is a 'sweet spot' for audio. Like every new Marantz AV Receiver this year, the SR6010 has WiFi and Bluetooth built-in and it supports Apple lossless, Gapless, FLAC HD 192/24 and even DSD and AIFF network streaming. Spotify Connect and AirPlay audio streaming are on board too. But we haven't changed everything. We've kept the staggering impact of audio quality, which is quite simply an intoxicating mix of effortless power, amazing detail and sensational depth: all thanks to the use of current feedback technology, HDAM pre-amplification and, of course, the 185W for each channel. And to get it all up and running effortlessly, there's a handy Setup Assistant.

#### Main Features

- Wi-Fi and Bluetooth built in
- Dolby Atmos and DTS:X (ready)
- 7ch discrete power amplifier, 185W per channel
- 13.2 ch preout (XLR 11.2) with 9.2 ch processing
- Current Feedback circuitry with Marantz New HDAM
- Audyssey MultEQ XT32, LFC, Sub EQ HT, Pro ready
- Latest HDMI 2.0a with 4K 60Hz 4:4:4 resolution
- 7+1 HDMI in / 2 out (4K 60Hz, 3D, ARC, HDR, BT2020)
- Full HDCP 2.2 support on all inputs
- HDMI scaling 1080p, 4k 50/60Hz
- MP3, WAV, AAC, WMA, AIFF
- HD Audio streaming: FLAC 192/24, DSD, ALAC
- Gapless Playback
- Spotify Connect\*, Internet Radio support
- Phono (MM) input
- Setup Assistant and advanced GUI
- Big trapdoor design; Aluminum front panel
- Marantz Remote App for iOS and Android devices
- ECO mode

#### EAN

EU	SR6010/N1B	4951035056622	Black
	SR6010/N1SG	4951035056639	Silvergold
UK	SR6010/T1B	4951035056622	Black
	SR6010/T1SG	4951035056639	Silvergold

www.marantz.eu



# because music matters

## SR6010

### NETWORK AV RECEIVER WITH WIFI & BLUETOOTH



FEATURES	SR6010
<b>MULTICHANNEL SURROUND</b>	
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	• / • / • / •
Dolby Digital Plus / Dolby TrueHD / Dolby Surround	• / • / •
Dolby Atmos	•
DTS:X	• (ready)
Multichannel Stereo	•
Compressed audio Enhancer: MDAx2	•
<b>NETWORK</b>	
DLNA Certified	• (v1.5)
Lossy formats MP3 / WMA / AAC	• / • / •
DSD Streaming	• (2.8 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 96/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay audio streaming	•
Windows PlayTo / Windows 8/RT compatible	• / •
Internet Radio (vTuner) / Spotify Connect *	• / •
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna)
<b>CONVENIENT AND SOUND</b>	
FM / AM Tuner	• / •
Current Feedback Topology	•
Hyper Dynamic Amplifier Modules (HDAM)	•
High grade audio components	•
Bluetooth	•
Auto speaker setup by microphone	Audyssey Mult EQ XT32 (Pro)
Audyssey Dynamic EQ / Dynamic Volume	• / •
Video conversion	CVBS > HDMI; Comp > HDMI
Video processing	>1080p, 4k 50/60Hz
ISF Certification	•
HDMI pass-through on stand-by	•
3D video pass-through / Audio Return Channel	• / •
On Screen Display: Advanced GUI	•
GUI overlay on HDMI	•
Setup Assistant (English, German, French, Spanish, Italian, Dutch, Swedish, Polish, Russian)	•
Smart Select	4 presets
Variable cross over	•
Multiroom zones	2
Optimized Bass Redirection	•

\* This feature is not available in all countries.

INPUTS/OUTPUTS	
<b>VIDEO</b>	
Composite In / Out	3+1 / 1
Component In / Out	2 / 1
HDMI In / Out	7+1 / 2 (main + zone)
<b>AUDIO</b>	
Analogue In / Out	5+1 / 0
Digital Optical In	2
Digital Coaxial In	2
Multichannel Pre Out	• (13.2, 9.2 processing)
Subwoofer Out	2
Zone audio preout	•
7.1 multichannel input	•
<b>OTHERS</b>	
Gold-plated terminals	•
Speaker A / B	•
Height speaker terminal	Speaker B or Height
Bi-amp drive	•
Multi-Room Speaker Terminal	Surround Back assignable
RS232 control	•
IR Flasher In	•
DC Trigger output	•
Marantz remote bus	•
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio / Made for iPod / Made for iPhone	• / • / •
<b>GENERAL</b>	
Available colours: Black / Silver-Gold	• / •
System Remote Control	RC025SR
Power Consumption in W	650
Power Consumption No-Sound (ECO ...on/off) in W	50 / 95
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in mm	440 x 398 x 161
Weight in kg	11.4

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: [www.spotify.com/connect/](http://www.spotify.com/connect/) third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

\* All specs can be subject to change.